

(12) INTERNATIONAL APPLICATION PUBLISHED UNDER THE PATENT COOPERATION TREATY (PCT)

(19) World Intellectual Property Organization
International Bureau



(43) International Publication Date
25 July 2002 (25.07.2002)

PCT

(10) International Publication Number
WO 02/057728 A1

(51) International Patent Classification⁷:
G01P 15/10, G01C 19/56, H03H 9/21

G01L 1/10,

(74) Agents: HALSNE, Eric et al.; Honeywell International Inc., 101 Columbia Road, P.O. Box 2245, Morristown, NJ 07962-2245 (US).

(21) International Application Number: PCT/US01/22581

(22) International Filing Date: 17 July 2001 (17.07.2001)

(84) Designated States (*regional*): European patent (AT, BE, CH, CY, DE, DK, ES, FI, FR, GB, GR, IE, IT, LU, MC, NL, PT, SE, TR).

(25) Filing Language: English

(26) Publication Language: English

(30) Priority Data:
60/262,470 17 January 2001 (17.01.2001) US

Declarations under Rule 4.17:

- as to the identity of the inventor (Rule 4.17(i)) for the following designations European patent (AT, BE, CH, CY, DE, DK, ES, FI, FR, GB, GR, IE, IT, LU, MC, NL, PT, SE, TR)
- as to applicant's entitlement to apply for and be granted a patent (Rule 4.17(ii)) for the following designations European patent (AT, BE, CH, CY, DE, DK, ES, FI, FR, GB, GR, IE, IT, LU, MC, NL, PT, SE, TR)
- as to the applicant's entitlement to claim the priority of the earlier application (Rule 4.17(iii)) for all designations

(71) Applicant: HONEYWELL INTERNATIONAL INC.
[US/US]; Law Department, 101 Columbia Road, P.O. Box 2245, Morristown, NJ 07962-2245 (US).


(72) Inventor: BLAKE, Graeme; 127 - 162nd Avenue SE, Bellevue, WA 98008 (US).

Published:

- with international search report

[Continued on next page]

(54) Title: DOUBLE RESONATING BEAM FORCE TRANSDUCER WITH REDUCED LONGITUDINAL PUMPING



(57) Abstract: A resonator beam structure that, during vibration of the tines, minimizes coupling of a longitudinal motion of the tines into a support structure to which the resonator beam is attached. The resonator beam includes a pair of tines; a first base region mechanically coupling a first ends of the tines together; a second base region mechanically coupling the second ends of the tines together; a first cutout of a first predetermined geometry at a first predetermined position in a closed interior portion of the first base region; and a second cutout of a second predetermined geometry at a second predetermined position in a closed interior portion of the second base region. The invention includes a method for using finite element analysis to determine an optimum geometry and position of the cutouts.

WO 02/057728 A1



For two-letter codes and other abbreviations, refer to the "Guidance Notes on Codes and Abbreviations" appearing at the beginning of each regular issue of the PCT Gazette.

**DOUBLE RESONATING BEAM FORCE TRANSDUCER WITH REDUCED
LONGITUDINAL PUMPING**

5

FIELD OF THE INVENTION

10 The present invention relates generally to double resonating beam force transducers and double ended tuning fork (DETF) sensors, and in particular to double resonating beam force transducers and DETF sensors decoupled from a support structure and a method of determining a decoupled resonator beam structure.

15

BACKGROUND OF THE INVENTION

 Typical double resonating beam force transducers and double ended tuning fork (DETF) sensors have two tines having constant widths. The tines terminate in solid base regions at each end of the beam, where the beam is tied into the support structure of the transducer. The tine terminations may be of various shapes, as
20 described in U.S. Patent No. 4,724,351 to Eernisse et al, which is incorporated in its entirety herein by reference. The Eernisse et al patent also describes tines of non-constant width.

 A problem arises when the resonator beam is vibrated: the longitudinal motion of the ends of the tines is coupled through base regions to the support structure
25 of the transducer. This coupling acts to reduce the Q factor of the resonator beam, and changes the resonator beam's frequency. The continual transfer of energy from the resonator to the surrounding structure due to longitudinal motion of the base regions is commonly referred to as an "end pumping" effect.

Other double resonating beam force transducers and double ended tuning fork (DETF) sensors have two constant-width tines with additional lateral teeth to aid in driving the resonator beam through electrical attraction to similar toothed structures. The additional lateral driver teeth on the tines tends to increase the end
5 pumping effect of the coupling.

An additional problem arises in devices having multiple resonators, which is common in accelerometers and similar devices. The coupling of one resonator into the support structure can transmit energy to the other resonators in the device and change their frequency. These changes in frequency lead to errors in indicated force.

10 Prior art solutions, such as those disclosed in the Eernisse et al patent, for reducing the effects of coupling have been to stiffen the midsection of the tines, shape the tine cross section, or modify the root of the tine near the base region where the beam is connected to the support structure. However, forming such irregular tine shapes presents manufacturing challenges.

15

SUMMARY OF THE INVENTION

The present invention provides a resonator beam that overcomes the limitations of the prior art by providing a resonator beam structure that, during vibration of the tines, minimizes coupling of a longitudinal motion of the tines into a support
20 structure to which the resonator beam is attached. The resonator beam includes a pair of tines having a first and a second end; a first base region mechanically coupling together the first ends of the tines; a second base region mechanically coupling together the second ends of the tines; a first cutout at a first predetermined position in a closed interior portion of the first base region and having a first predetermined geometry; and a
25 second cutout at a second predetermined position in a closed interior portion of the second base region and having a second predetermined geometry.

The first and second predetermined positions are positions that are predetermined to minimize, during vibration of the tines, coupling of the longitudinal motion of the tines into a support structure to which the resonator beam is attached. The

predetermined position of the first cutout is a position that is adjacent to the first end of the tines; and the predetermined position of the second cutout is a position that is adjacent to the second end of the tines.

The first and second predetermined geometries are geometries that are
5 predetermined to minimize, during vibration of the tines, coupling of the longitudinal motion of the tines into a support structure to which the resonator beam is attached. The predetermined geometries are, for example, rectangular shapes having respective first and second predetermined sizes. The first and second predetermined geometries are, for example, substantially identical.

10 The invention also provides a method using finite element analysis techniques for determining optimal geometries and positions for cutouts in the enlarged or widened base regions of the resonator beam structure that, during vibration of the tines, minimizes coupling of a longitudinal motion of the tines into a support structure to which the resonator beam is attached.

15

BRIEF DESCRIPTION OF THE DRAWINGS

The foregoing aspects and many of the attendant advantages of this invention will become more readily appreciated as the same becomes better understood by reference to the following detailed description, when taken in conjunction with the
20 accompanying drawings, wherein:

Figure 1 shows the invention embodied as a transducer having a DETF resonator beam with cutouts of a predetermined size formed at a predetermined position;

Figure 2 is a flow chart showing the method of the invention as
25 embodied in determining optimal cutout geometry and position that minimizes coupling of tine longitudinal motion into a support structure of a resonator beam by modeling;

Figure 3 is a graph showing data developed during practice of the method of the invention;

Figure 4 shows a coded matrix developed during practice of the method of the invention;

Figure 5 shows a results matrix corresponding to the coded matrix shown in Figure 4 and found using a finite element analysis program during practice of the
5 method of the invention;

Figure 6 shows values for coefficients used in an equation for determining the average displacement of the tines in a vibrating resonator beam; and

Figures 7A-7E are graphs showing data developed during practice of the method of the invention.

10

DETAILED DESCRIPTION OF PREFERRED EMBODIMENT

In the Figures, like numerals indicate like elements.

The present invention is a resonator beam apparatus having interior cutouts in a base region of the resonator beam for reducing longitudinal pumping
15 effects. The cutouts are formed within the interior of the base region that couples the tines together and are completely surrounded by the material of the base region.

The present invention also provides a method of determining optimal cutout geometry and position for minimizing coupling of tine longitudinal motion into a support structure. The interior cutouts are thus of a predetermined size and are formed at
20 a predetermined position in the base region of the beam near the termination of the tines.

Figure 1 shows the invention embodied as a transducer 100 having a DETF resonator beam 110 with cutouts 112 of a predetermined size formed at a predetermined position. The DETF resonator beam 110 has a pair of generally parallel
25 tines 114, 116 having substantially constant widths. The two tines 114, 116 are coupled together at enlarged or widened base regions 118, 120 and are separated from each other by a slot 122 to form a double ended tuning fork. The resonator beam 110 is separated from a frame portion 124 of the transducer 100 so that the tines 114, 116 may be vibrated laterally relative to fixed base regions 118, 120, as is generally known in the art

and described in the Eernisse et al patent. In an accelerometer device, the base regions 118, 120 are suitably bonded to a pendulous proof mass 126 and the frame 124, respectively, by mounting pads 128, 130. The widened base regions 118, 120 mechanically couple the vibrating tines 114, 116 to each other.

5 As shown in Figure 1, the resonator beam 110 may include lateral teeth as part of an electrostatic drive for laterally vibrating the tines 114, 116 at the resonance frequency. The electrostatic drive includes a pair of elongate drive electrodes (not shown) spaced away on either side of the tines 114, 116. However, the invention is equally applicable to resonator beams that are not vibrated by an electrostatic drive and
10 do not include the lateral teeth shown in Figure 1.

 In contrast to the solutions of the prior art, the cutouts 112 of the present invention are internal cutouts formed in the base regions 118, 120 between the tines 114, 116. In other words, the cutouts 112 are completely surrounded by material forming the respective the base regions 118, 120. The size or geometry and the position
15 within the base regions 118, 120 of the cutouts 112 are determined according to the method of the invention to minimize or eliminate coupling of the longitudinal motion of the ends of the tines 114, 116 to the support structure of the transducer when the resonator beam 110 is vibrated, which minimizes or eliminates the end pumping effect.

 The method of the invention is practiced by modeling resonator beam
20 structures having rectangular cutouts 112. Although the invention is believed to be equally applicable to alternatively shaped cutouts, rectangular cutouts 112 have been used in the practice of the invention for ease of model construction. The invention is also practiced with cutouts 112 that are substantially identical in size and shape. Optimization can be accomplished using a FEA (finite element analysis) program, such
25 as any of the known programs, by varying the size and position parameters of the cutouts 112 while monitoring longitudinal end pumping.

 Optimization is accomplished by determining the geometry and position of cutouts that provide sufficient coupling between the two tines 114, 116 such that the in-plane, out-of-phase vibration of the tines remains a normal mode, while the coupling

of the vibration to the "outside world," as evidenced by end pumping effects, is reduced to a minimum.

Figure 2 is a flow chart showing the method 200 of the invention as embodied in determining optimal cutout geometry and position that minimizes coupling of longitudinal motion of the tines 114, 116 into a support structure for an exemplary resonator beam 110 by modeling. The method 200 of the invention is equally applicable to other resonator beam structures, including resonator beams having tines of various shapes.

According to the method of the invention as embodied in a FEA program such as ANSYS, in a model of the resonator beam 110 having one of the base regions 118, 120 fixed, cutouts 112 of a predetermined size or geometry are applied at a predetermined position in the base regions 118, 120 at which the tines 114, 116 terminate, as shown in Block 210. The cutouts 112 in the respective base regions 118, 120 may be the same size and configuration. The normal modes of the resonator beam 110 are computed in Block 220. A ratio R is computed in Block 230 of the amplitude of the longitudinal motion of the free one of base region 118, 120 to the amplitude of the center of the tines 114, 116 in the mode used for force sensing (in-plane, out-of-phase tine motion). The amplitude ratio R computed in Block 230 is a measure of the relative effectiveness of the cutouts 112 in reducing end pumping effects. Small values for the ratio R indicate increasing effectiveness.

The amplitude ratio R is computed using the finite element analysis model to compute an amplitude of a longitudinal motion of the free one of base region 118, 120; using the finite element analysis model to compute an amplitude of the center of the tines 114, 116; and computing the ratio R of the two amplitudes. The ratio R is thus the ratio of the end motion over the tine motion.

In Block 240 the amplitude ratio R is compared with a desired minimum value indicative of an optimal cutout 112 geometry and position for the application of interest. For example, the amplitude ratio R is compared to zero. If the value of the amplitude ratio R is sufficiently close to zero, the predetermined sizes and positions of the cutouts 112 are acceptable.

If the value of the amplitude ratio R is too large to satisfy the requirements of the application, the method can be practiced iteratively. In Block 250 one or both of the size and position of the cutouts 112 are adjusted. The new size and position values for the cutouts 112 are applied to the model in Block 210, and the
5 normal modes of the resultant resonator beam are recomputed in Block 220. The amplitude ratio R is recomputed in Block 230, and the value of the recomputed amplitude ratio R is analyzed in Block 240. The method is thus practiced iteratively until optimal size and position values for the cutouts 112 are determined, as indicated by an acceptable value of the amplitude ratio R.

10 The reduced end pumping effects are optionally verified in a full model of the accelerometer sensor die in which the resonator beam 110 is utilized, as shown in Block 260.

According to one exemplary implementation of the method of the invention, size or geometry and position parameters are determined for the cutouts 112
15 in the in the base regions 118, 120 of a resonator beam 110 of a DETF near the termination of the tines 114, 116. The cutouts 112 are rectangular. In determining the size or geometry and position parameters, three factors are considered: the distance between the ends of the tines 114, 116 and the near end of the cutout 112, the distance between the ends of the tines 114, 116 and the far end of the cutout 112, and the width
20 of the cutout 112.

The base resonator beam 110 is substantially fixed to dimensions near those actually used for one proprietary DETF application, wherein:

Tine length: 1395 micron;
Tine width: 26 micron;
25 Space between tines: 26 micron;
Eernisse's L/M ratio: 1.25;
Base extension for mounting: 50 micron;
Number of teeth: 33;
Pitch of teeth: 22 micron;
30 Width of teeth: 5 micron;

Length of teeth: 28 micron; and

DETF thickness: 18.5 micron.

The distances from the horizontal edges of the cutouts 112 to the ends of the tines 114, 116 are expressed as equivalent L/M ratios according to the Eernisse
5 definition, LM1 and LM2, where M is the length of the tines 114, 116 between the base regions 118, 120; and L is the length of the tines 114, 116 plus the length of the base regions 118, 120 between the mounting pads 128, 130.

The distance from the DETF center to the closest edge is $LM1 * Lt/2$, where Lt is the length of the tines 114, 116. The distance from the center of the DETF
10 100 to the edge of the furthest cutout 112 is $LM2 * Lt/2$. The width of the cutout 112 is expressed as a fraction, HRatio, of the total width of the base region 118, 120, such that the actual width of the cutout 112 is equal to $HRatio * WBase$, where WBase is the width of the base region 118, 120.

The FEA model is constructed and analyzed in ANSYS or another FEA
15 program. In the FEA model, the base region 118 at one end of the DETF 100 is fixed. The base region 120 at the other end is minimally constrained to slide. The average displacement of the end of the minimally constrained mounting base region 120 in the axial direction is computed for the in-plane, out-of-phase mode, and normalized by dividing it by the in-plane displacement of a tine node at the center of the inside edge.
20 The normalized value is used as a measure of the end pumping effect.

Figure 3 is a graph showing data for a case in which the values of HRatio and LM2 are both fixed, and the material is isotropic. For the case graphed in Figure 3, HRatio = 0.5, i.e., the cutout 112 is half the width of the base region 118, 120, and LM2 = 1.2, i.e., the far edge of the cutout 112 corresponds to $L/M = 1.2$.

25 The normalized displacements, NUY, versus LM1 values, are given by:

$$R = \begin{pmatrix} 1.05 & 1.07 & 1.08 & 1.088 & 1.092 & 1.095 & 1.1 \\ 2.033 \times 10^{-3} & 5.923 \times 10^{-4} & 2.103 \times 10^{-4} & -3.076 \times 10^{-6} & -1.038 \times 10^{-4} & -1.558 \times 10^{-4} & -2.417 \times 10^{-4} \end{pmatrix}^T$$

where the first row of the matrix is filled by the LM1 values and the second row is filled by the NUY values. The graph in Figure 3 shows a zero crossing near LM1 = 1.088.

The curve of the data suggests that the dependence of NUY on LM1 is best modeled as a quadratic. The other factors, LM2 and HRatio, may also be best modeled as quadratic.

- 5 A full quadratic DOE (design of experiments) model requires 27 runs. A DOE model, however, is less accurate than estimating the NUY values directly. A DOE model is useful for determining starting values for LM1, LM2, and HRatio to use in the direct FEA analysis. Thus, while a DOE approach is useful, one or more final FEAs are needed to find the best NUY values.

- 10 According to the present embodiment of the invention, the limits on the variables are: $0.25 \leq \text{HRatio} \leq 0.75$; $1.025 \leq \text{LM1} \leq 1.15$; and $1.175 \leq \text{LM2} \leq 1.225$.

The value table can be expressed as:

$$\text{Vars} = \begin{pmatrix} 1.025 & 1.0875 & 1.15 \\ 1.175 & 1.2 & 1.225 \\ 0.25 & 0.5 & 0.75 \end{pmatrix} \quad \begin{pmatrix} -1 & 0 & 1 \\ -1 & 0 & 1 \\ -1 & 0 & 1 \end{pmatrix} \begin{matrix} \text{LM1} \\ \text{LM2} \\ \text{HRatio} \end{matrix}$$

The coded matrix design D is shown in Figure 4.

- 15 The corresponding results matrix RES found using the FEA program is shown in Figure 5.

- The model is conveniently analyzed using the MATHCAD© analysis program or another analysis program. The model is analyzed in terms of three coded factors: A (LM1), B (LM2), and C (HRatio). Coded values are created corresponding to
20 the results. These values are used as X values for a regression fit.

All the terms determined by solving for the model coefficients contribute significantly to the value of the average displacement of the ends of the tines 114, 116, i.e., end pumping effect. The formula for this displacement, NUY, can be written as:

$$\begin{aligned} \text{NUY(A, B, C)} := & \text{Coeff}_0 * A + \text{Coeff}_1 * B + \text{Coeff}_2 * C + \text{Coeff}_3 * A * B \dots \\ & + \text{Coeff}_4 * A * C + \text{Coeff}_5 * B * C + \text{Coeff}_6 * A \dots \\ & + \text{Coeff}_7 * B^2 + \text{Coeff}_8 * C^2 \end{aligned}$$

where: Coeff₀ through Coeff₈ have values shown in Figure 6.

The values of NUY are plotted in Figures 7A-7E for various fixed C values (HRatio values), varying A (LMI) and B (LM2), in order to determine combinations of values that result in a minimum or zero value for NUY. For example, using a moderately fine grid having $m := 0 \dots 20$ and $n := 0 \dots 20$, for all cases $A_m := -1 + m/10$ and $B_n := -1 + n/10$, plots are generated for five C values: -1, -0.5, 0, +0.5, and +1.0. That is: $C_{m1} := -1.0$, $C_{mp5} := -0.5$, $C_0 := 0$, $C_{pp5} := +0.5$, and $C_{p1} := +1.0$. The five plot matrices are:

- Figure 7A is a plot of $NUY_{m1,n} := NUY(A_m, B_n, C_{m1})$,
 Figure 7B is a plot of $NUY_{mp5,n} := NUY(A_m, B_n, C_{mp5})$,
 10 Figure 7C is a plot of $NUY_{0,n} := NUY(A_m, B_n, C_0)$,
 Figure 7D is a plot of $NUY_{pp5,n} := NUY(A_m, B_n, C_{pp5})$, and
 Figure 7E is a plot of $NUY_{p1,n} := NUY(A_m, B_n, C_{p1})$.

Inspection of the plotted values shows at least one line of feasible points in each plot. A few points are selected for checking. For example, in the plot shown in
 15 Figure 7A having HRatio=0.25, the point $LM1=1.041$ and $LM2=1.2$ is selected. In the plot shown in Figure 7C having HRatio=0.5, the point $LM1=1.087$ and $LM2=1.2$ is selected. In the fifth plot shown in Figure 7E having HRatio=0.75, the point $LM1=1.133$ and $LM2=1.2$ is selected. These points are expected to have NUY values near zero. In fact, the values predicted by the formula are given by:

$$\text{Predicted} := \begin{pmatrix} NUY\left(-1 + \frac{1.041 - 1.025}{0.125} * 2, 0, -1\right) \\ NUY\left(-1 + \frac{1.087 - 1.025}{0.125} * 2, 0, 0\right) \\ NUY\left(-1 + \frac{1.133 - 1.025}{0.125} * 2, 0, 1\right) \end{pmatrix} \quad \text{Predicted} := \begin{pmatrix} -3.015 * 10^{-5} \\ -3.859 * 10^{-5} \\ -2.715 * 10^{-5} \end{pmatrix}$$

The selection of LM1, LM2, and HRatio values from plots is limited in accuracy; the desire is that all predicted values are zero. The FEA values generated by ANSYS for the selected LM1, LM2, and HRatio values are given by:

$$FEA := \begin{pmatrix} 4.67 \cdot 10^{-4} \\ 1.891 \cdot 10^{-5} \\ 4.937 \cdot 10^{-4} \end{pmatrix}$$

The FEA and Predicted values are compared for differences and ratios.

5 These comparisons yield:

$$FEA - Predicted := \begin{pmatrix} 4.971 \cdot 10^{-4} \\ -1.968 \cdot 10^{-5} \\ 5.209 \cdot 10^{-4} \end{pmatrix} \quad \text{and} \quad \frac{\overrightarrow{FEA}}{Pr edicted} = \begin{pmatrix} -15.491 \\ 0.49 \\ -18.183 \end{pmatrix}$$

In determining the effectiveness of the cutouts 112, the reduction in the NUY value is compared before and after the cutouts 112 are added. In the present example, the NUY value of the DETF before addition of the cutouts 112 is

NUY = - 6.834 · 10⁻⁴. The magnitude of the reduction in NUY when the cutouts 112

10 are added is compared with the magnitude of the error. The calculation yields:

$$\left| \frac{\overrightarrow{FEA} - Pr edicted}{-6.834 \cdot 10^{-4} - FEA} \right| = \begin{pmatrix} 0.432 \\ 0.028 \\ 0.442 \end{pmatrix}$$

Small values indicate increasing effectiveness. Accordingly, the case having HRatio=0.5 (0.028 element) is expected to be effective, which the other cases are not.

The second calculation compares the predicted reduction ratios to those obtained with the cutout 112. Values near 1 indicate that the obtained reduction ratios are near the predicted reduction ratios. The obtained reduction ratio is given by:

$$\text{Obtained ratio} := \left| \frac{\overrightarrow{-6.834 * 10^{-4}}}{FEA} \right| \quad \text{and} \quad \text{Obtained ratio} := \begin{pmatrix} -1.463 \\ -36.14 \\ -1.384 \end{pmatrix}$$

$$\text{Predicted ratio} := \left| \frac{\overrightarrow{-6.834 * 10^{-4}}}{Pr edicted} \right| \quad \text{and} \quad \text{Predicted ratio} := \begin{pmatrix} 22.67 \\ -17.709 \\ 25.169 \end{pmatrix}$$

5

The ratio of the ratios is given by:

$$\frac{\overrightarrow{Pr edicted . ratio}}{Obtained . ratio} = \begin{pmatrix} -15.491 \\ 0.49 \\ -18.183 \end{pmatrix}$$

The ratio of the predicted ratio to the obtained ratio is equal to: $\frac{\overrightarrow{FEA}}{Pr edicted}$. The middle value is near zero and is therefore predictive of the cutout being effective in reducing or eliminating the end pumping effect.

10

While the preferred embodiment of the invention has been illustrated and described, it will be appreciated that various changes can be made therein without departing from the spirit and scope of the invention.

The embodiments of the invention in which an exclusive property of privilege is claimed are defined as follows:

CLAIMS

1. A resonator beam, comprising:
 - 5 a pair of tines having a first and a second end;
a first base region mechanically coupling together the first ends of the tines;
a second base region mechanically coupling together the second ends of the tines;
a first cutout at a first predetermined position in a closed interior portion of the
 - 10 first base region and having a first predetermined geometry; and
a second cutout at a second predetermined position in a closed interior portion of the second base region and having a second predetermined geometry.
2. The resonator of claim 1, wherein the first and second predetermined positions are positions that are predetermined to minimize, during vibration of the tines, coupling
- 15 of a longitudinal motion of the tines into a support structure to which the resonator beam is attached.
3. The resonator of claim 2, wherein the first and second predetermined geometries are geometries that are predetermined to minimize, during vibration of the tines, coupling of the longitudinal motion of the tines into a support structure to which the
- 20 resonator beam is attached.
4. The resonator of claim 3, wherein:
 - the first predetermined position of the first cutout is a position that is adjacent to the first end of the tines; and
 - the second predetermined position of the second cutout is a position that is
 - 25 adjacent to the second end of the tines.

5. The resonator of claim 1, wherein the first and second predetermined positions and the first and second predetermined geometries are predetermined using finite element analysis.
6. The resonator of claim 1, wherein the first and second predetermined geometries
5 are rectangular shapes having respective first and second predetermined sizes.
7. The resonator of claim 1, wherein the first and second predetermined geometries are substantially identical.
8. A resonator beam, comprising:
two elongated tines having substantially constant widths, the beams spaced apart
10 and terminated at first and second ends in respective first and second integral base regions;
first and second cutouts positioned in the respective first and second base regions between and adjacent to the respective first and second ends of the tines, the cutouts completely surrounded by material forming the respective first and second base
15 regions.
9. The resonator beam of claim 8, wherein the first and second cutouts in the respective first and second base regions are positioned at positions predetermined using a finite element analysis program to minimize coupling of a vibration of the tines into a support structure to which the resonator beam is attached.
- 20 10. The resonator beam of claim 8, wherein each of the first and second cutouts is rectangular in shape.
11. The resonator beam of claim 8, wherein the first and second cutouts are substantially identical in size and shape.

12. In a resonator beam having two tines terminating in base regions, a method for minimizing coupling of vibration of the resonator beam into a support structure to which the resonator beam is attached, the method comprising:

- in a model of the resonator beam having one of the base regions fixed and an
5 other of the base regions free, applying a cutout of a predetermined geometry at a predetermined position in an interior portion of each of the base regions;
computing normal resonance modes of the resonator beam;
computing a ratio of an amplitude of a longitudinal motion of the free base region to an amplitude of the center of the tines; and
10 comparing the ratio with a desired minimum value.

13. The method of claim 12, wherein the comparing the ratio with a desired minimum value indicates an acceptable result, further comprising verifying the result.

14. The method of claim 13, wherein verifying the results includes testing a model of an accelerometer die in which the resonator beam is utilized.

- 15 15. The method of claim 12, wherein computing a ratio of an amplitude of a longitudinal motion of the free base region to an amplitude of the center of the tines comprises:

computing an amplitude of a longitudinal motion of the free base region; and
computing an amplitude of the center of the tines.

- 20 16. The method of claim 15, wherein both of the amplitude of a longitudinal motion of the free base region and the amplitude of the center of the tines are computed in a mode used for force sensing.

17. The method of claim 12, further comprising:
determining different cutouts having one of a different geometry and a different
25 position;
applying the different cutouts to the model of the resonator beam; and

computing normal resonance modes of the resonator beam having the different cutouts;

in the model of the resonator beam having the different cutouts, computing a ratio of an amplitude of a longitudinal motion of the free base region to an amplitude of the center of the tines; and

comparing the ratio with the desired minimum value.

18. The method of claim 17, repeating the determining, applying, computing, and comparing until the comparing the ratio with a desired minimum value indicates an acceptable result.

19. In a resonator beam having two tines terminating in base regions, a method for minimizing coupling of vibration of the resonator beam into a support structure to which the resonator beam is attached, the method comprising:

in a finite element analysis model of the resonator beam having one of the base regions fixed and an other of the base regions free, applying a first cutout of a predetermined size at a predetermined position in an interior portion of a first one of the base regions, and applying a second cutout of a predetermined size at a predetermined position in an interior portion of a second one of the base regions;

using the finite element analysis model, computing normal resonance modes of the resonator beam;


using the finite element analysis model, computing an amplitude of a longitudinal motion of the free base region;

using the finite element analysis model, computing an amplitude of the center of the tines;



computing a ratio of an amplitude of a longitudinal motion of the free base region to an amplitude of the center of the tines in the mode used for force sensing; and comparing the ratio to zero.

20. The method of claim 19, further comprising:
changing one of the predetermined size and the predetermined position of at least one of the cutouts; and
repeating the steps of the method.
- 5 21. The method of claim 20, further comprising: repeating the steps of the method until the ratio approaches zero.

1/6

*Fig. 1*

2/6



3/6

$$D:= \begin{bmatrix} 1 & 1 & 1 \\ 1 & 1 & 0 \\ 1 & 1 & -1 \\ 1 & 0 & 1 \\ 1 & 0 & 0 \\ 1 & 0 & -1 \\ 1 & -1 & 1 \\ 1 & -1 & 0 \\ 1 & -1 & -1 \\ 0 & 1 & 1 \\ 0 & 1 & 0 \\ 0 & 1 & -1 \\ 0 & 0 & 1 \\ 0 & 0 & 0 \\ 0 & 0 & -1 \\ 0 & -1 & 1 \\ 0 & -1 & 0 \\ 0 & -1 & -1 \\ -1 & 1 & 1 \\ -1 & 1 & 0 \\ -1 & 1 & -1 \\ -1 & 0 & 1 \\ -1 & 0 & 0 \\ -1 & 0 & -1 \\ -1 & -1 & 1 \\ -1 & -1 & 0 \\ -1 & -1 & -1 \end{bmatrix}$$

Fig.4 $RES:=10^{-4}*$



$$\begin{bmatrix} -6.04903 \\ -6.18054 \\ -6.49559 \\ -6.16593 \\ -6.20150 \\ -6.47571 \\ -6.19634 \\ -6.19621 \\ -6.46493 \\ 4.68590 \\ 4.14590 \times 10^{-2} \\ -4.49744 \\ 4.74662 \\ 0.135877 \\ -4.20176 \\ 4.53394 \\ 6.64544 \times 10^{-2} \\ -4.19338 \\ 216.749 \\ 0.734371 \\ 9.63027 \\ 213.197 \\ 71.2335 \\ 10.24755 \\ 207.580 \\ 67.5859 \\ 9.60993 \end{bmatrix}$$

Fig.5



$$COEFF= \begin{bmatrix} -4.794 \times 10^{-3} \\ -3.206 \times 10^{-4} \\ 3.533 \times 10^{-3} \\ 4.816 \times 10^{-4} \\ -5.058 \times 10^{-3} \\ 8.152 \times 10^{-5} \\ 3.667 \times 10^{-3} \\ -9.192 \times 10^{-4} \\ 1.669 \times 10^{-3} \end{bmatrix}$$

Fig.6


4/6

NUY: X=LM1, Y=LM2, HRATIO=0.25*Fig. 7A**NUY: X=LM1, Y=LM2, HRATIO=0.375**Fig. 7B*

5/6

*Fig. 7C**Fig. 7D*

6/6

*Fig. 7E*

INTERNATIONAL SEARCH REPORT

International Application No

PCT/US 01/22581

A. CLASSIFICATION OF SUBJECT MATTER

IPC 7 G01L1/10 G01P15/10 G01C19/56 H03H9/21

According to International Patent Classification (IPC) or to both national classification and IPC

B. FIELDS SEARCHED

Minimum documentation searched (classification system followed by classification symbols)

IPC 7 G01L G01P G01C H03H

Documentation searched other than minimum documentation to the extent that such documents are included in the fields searched

Electronic data base consulted during the International search (name of data base and, where practical, search terms used)

PAJ, EPO-Internal, WPI Data

C. DOCUMENTS CONSIDERED TO BE RELEVANT

Category *	Citation of document, with indication, where appropriate, of the relevant passages	Relevant to claim No.
X Y A	EP 0 030 741 A (PAROSCIENTIFIC, INC.) 24 June 1981 (1981-06-24) page 7, line 31 -page 8, line 7; figure 8	1-4, 6-8, 10, 11 5, 9 12, 19
Y	WO 95 31859 A (ALLIEDSIGNAL, INC.) 23 November 1995 (1995-11-23) abstract; figures	5, 9
X	US 4 299 122 A (T. UEDA ET AL.) 10 November 1981 (1981-11-10) column 3, line 41 -column 4, line 14; figures 4A, 5A	1-4, 7, 8, 11
X	WO 88 00334 A (SENSOR INTERNATIONAL) 14 January 1988 (1988-01-14) page 10, paragraph 3 -page 12, paragraph 2; figures 5, 6	1

-/--

☒ Further documents are listed in the continuation of box C.☒ Patent family members are listed in annex.

* Special categories of cited documents:

A document defining the general state of the art which is not considered to be of particular relevance

E earlier document but published on or after the International filing date

L document which may throw doubts on priority claim(s) or which is cited to establish the publication date of another citation or other special reason (as specified)

O document referring to an oral disclosure, use, exhibition or other means

P document published prior to the International filing date but later than the priority date claimed

T later document published after the International filing date or priority date and not in conflict with the application but cited to understand the principle or theory underlying the invention

X document of particular relevance; the claimed invention cannot be considered novel or cannot be considered to involve an inventive step when the document is taken alone

Y document of particular relevance; the claimed invention cannot be considered to involve an inventive step when the document is combined with one or more other such documents, such combination being obvious to a person skilled in the art.

& document member of the same patent family

Date of the actual completion of the International search

21 January 2002

Date of mailing of the international search report

30/01/2002

Name and mailing address of the ISA

European Patent Office, P.B. 5818 Patentlaan 2
NL - 2280 HV Rijswijk
Tel. (+31-70) 340-2040, Tx. 31 651 epo nl,
Fax (+31-70) 340-3016

Authorized officer

Van Assche, P

INTERNATIONAL SEARCH REPORT

International Application No

PCT/US 01/22581

C.(Continuation) DOCUMENTS CONSIDERED TO BE RELEVANT

Category *	Citation of document, with indication, where appropriate, of the relevant passages	Relevant to claim No.
X	PATENT ABSTRACTS OF JAPAN vol. 015, no. 014 (E-1022), 11 January 1991 (1991-01-11) & JP 02 262874 A (RION CO LTD), 25 October 1990 (1990-10-25) abstract	1
A	----- US 4 658 174 A (W.C. ALBERT) 14 April 1987 (1987-04-14) abstract; figures -----	1,8

INTERNATIONAL SEARCH REPORT

Information on patent family members

International Application No

PCT/US 01/22581

Patent document cited in search report		Publication date	Patent family member(s)	Publication date
EP 30741	A	24-06-1981	US 4321500 A AT 9738 T CA 1141983 A1 DE 3069388 D1 EP 0030741 A2 JP 56132534 A	23-03-1982 15-10-1984 01-03-1983 08-11-1984 24-06-1981 16-10-1981
WO 9531859	A	23-11-1995	DE 69517976 D1 DE 69517976 T2 DE 759232 T1 EP 0759232 A1 IL 113556 A JP 10500482 T WO 9531859 A1 US 5668329 A	17-08-2000 28-12-2000 04-09-1997 26-02-1997 05-04-1998 13-01-1998 23-11-1995 16-09-1997
US 4299122	A	10-11-1981	JP 1221194 C JP 55051329 A JP 58056425 B	26-07-1984 15-04-1980 14-12-1983
WO 8800334	A	14-01-1988	AT 72897 T AU 600296 B2 AU 7695387 A CA 1264335 A1 DE 3776911 D1 EP 0313570 A1 JP 1501166 T JP 5079929 B KR 9204325 B1 US 4773493 A WO 8800334 A1 ZA 8704746 A BR 8704293 A CN 87105638 A , B	15-03-1992 09-08-1990 29-01-1988 09-01-1990 02-04-1992 03-05-1989 20-04-1989 05-11-1993 01-06-1992 27-09-1988 14-01-1988 27-04-1988 12-04-1988 22-06-1988
JP 02262874	A	25-10-1990	NONE	
US 4658174	A	14-04-1987	AU 6755287 A CA 1261929 A1 DE 3709096 A1 FR 2596152 A1 GB 2188149 A , B IL 80565 A IT 1203504 B JP 62229039 A NO 864954 A SE 8700008 A	24-09-1987 26-09-1989 24-09-1987 25-09-1987 23-09-1987 10-06-1990 15-02-1989 07-10-1987 21-09-1987 21-09-1987